DS001/DS001UK Sweex Docking Station

Introduction

First of all, many thanks for purchasing this Sweex Docking Station. With this docking station you can quickly and easily extend the connection facilities of the PC, while you only need 1 free USB port.

To ensure this product operates correctly, we advise you to carefully read this manual first. If despite this manual you still experience problems during installation or operation of this product, go to www.sweex.com and look under the heading service & support.

Contents of the box

Prior to installation, check if all required parts are present. The following parts must be present in the box:

- Docking station
- USB cable
- Mains supply adaptor
- CD-ROM with manual, drive and software

If one of the above parts is missing, please contact the supplier.

Specifications

- 1 x uplink USB-B port
- 2 x downlink USB-A 2.0
- Supports: PS/2 for keyboard and mouse
- 1 x serial port
- 1 x parallel port
- 1 x 10/100 Ethernet LAN port (RJ-45)
- 1 x USB-B file transfer host port (USB 1.1)

Additional specifications

- Dimensions: 187 x 73 x 27 mm (w x d x h)
- Weight: 200 grams
- Input voltage: DC 5V
- Input current: 1.2A
- Operating temperature: 0°~72°C
- Storage temperature: -10°~80°C
- Humidity level: 0~90%RH
- EMI: CE & FCC
- Supports: Windows ME, 2000 and XP

System requirements

- IBM-compatible PC
- Windows ME, 2000 or XP
- 1 available USB port
- 64 MB of RAM
- Pentium 233 MHz or higher

Installation

Before installing the docking station, it must have a power supply. This is done by connecting the docking station to the mains supply adaptor. Before connecting the PC to the docking station, the serial port driver must be installed. The link to this driver is shown in the menu that appears automatically when the CD-ROM is placed in the drive. If automatic start is disabled, the driver Serial Driver Installer.exe can be found on the CD-ROM in the "drivers" folder.

When executed, the following screen appears:


InstallShield Wizard
Welcome to the InstallShield Wizard for PL-2303 USB-to-Serial
The InstallShield® Wizard will install PL-2303 USB-to-Serial on your computer. To continue, click Next.
< Back
Next >
Cancel

Push the next button.


InstallShield Wizard
InstallShield Wizard Complete
InstallShield already successfully to installed PL-2303 USB to Serial driver. Please press (Finish) button to close and out of InstallShield.
If you have been plugged cable on PC before run this setup, please unplug and then plug cable again for system detect this device!
< Back
Finish
Cancel

Push Finish to complete the installation successfully.

Then the docking station must be connected to the computer by means of the USB-B cable supplied. Connect the USB-B cable to the Upstream port (next to the supply inlet).

Windows now automatically detects the hardware, and the following window will appear:

Found New Hardware Wizard
Welcome to the Found New Hardware Wizard
This wizard helps you install software for:
AV88772
If your hardware came with an installation CD or floppy disk, insert it now.
What do you want the wizard to do?
Install the software automatically (Recommended)
Install from a list or specific location (Advanced)
Click Next to continue.
< Back
Next >
Cancel

Select the second option and click on “next”.


Found New Hardware Wizard
Please choose your search and installation options.
Search for the best driver in these locations.
Use the check boxes below to limit or expand the default search, which includes local paths and removable media. The best driver found will be installed.
Search removable media (floppy, CD-ROM...)
Include this location in the search:
D:\drivers\
Browse
Don't search. I will choose the driver to install.
Choose this option to select the device driver from a list. Windows does not guarantee that the driver you choose will be the best match for your hardware.
< Back
Next >
Cancel

On the CD-ROM, look for the folder “Drivers” and select it.

Hardware Installation
The software you are installing for this hardware:
ASIX AX88772 USB2.0 to Fast Ethernet Adapter
has not passed Windows Logo testing to verify its compatibility with Windows XP. (Tell me why this testing is important.)
Continuing your installation of this software may impair or destabilize the correct operation of your system either immediately or in the future. Microsoft strongly recommends that you stop this installation now and contact the hardware vendor for software that has passed Windows Logo testing.
Continue Anyway
STOP Installation

During installation, click on "Continue anyway" if Windows requests this. Finally, click on finish in order to complete the installation of this component. A new component is detected automatically and generates the following window:

Found New Hardware Wizard
Welcome to the Found New Hardware Wizard
Windows will search for current and updated software by looking on your computer, on the hardware installation CD, or on the Windows Update Web site (with your permission).
Read our privacy policy
Can Windows connect to Windows Update to search for software?
Yes, this time only
Yes, now and every time I connect a device
No, not this time
Click Next to continue.
< Back
Next >
Cancel

Select "no, not at this moment" and click "next".


Found New Hardware Wizard
This wizard helps you install software for:
USB Device
If your hardware came with an installation CD or floppy disk, insert it now.
What do you want the wizard to do?
Install the software automatically (Recommended)
Install from a list or specific location (Advanced)
Click Next to continue.
< Back
Next >
Cancel

Select the second option and click on "next".


Found New Hardware Wizard
Please choose your search and installation options.
Search for the best driver in these locations.
Use the check boxes below to limit or expand the default search, which includes local paths and removable media. The best driver found will be installed.
Search removable media (floppy, CD-ROM...)
Include this location in the search:
D:\drivers\
Browse
Don't search. I will choose the driver to install.
Choose this option to select the device driver from a list. Windows does not guarantee that the driver you choose will be the best match for your hardware.
< Back
Next >
Cancel

On the CD-ROM, look for the folder “Drivers” and select it. Then click on “next”. Another window opens, i.e. that for the PCLinQ installation. See the chapter PCLinQ for more information. Finally, click on finish in order to complete the installation of this component.

PC Linq

PC Linq is the programme that enables you to exchange files between 2 PCs. To this end, connect the docking station (after it has been installed) to a second PC via the “Transfer” USB-B port.


InstallShield Wizard
Welcome to the InstallShield Wizard for PC-Linq
The InstallShield® Wizard will install PC-Linq on your computer. To continue, click Next.
< Back
Next >
Cancel

Click on “next” to continue.

InstallShield Wizard
Choose Destination Location
Select folder where Setup will install files.
Setup will install PC-Linq in the following folder.
To install to this folder, click Next. To install to a different folder, click Browse and select another folder.
Destination Folder
C:\Program Files\PC-Linq
Browse...
InstallShield
< Back
Next >
Cancel

Then select the location where you wish to install the programme. Click on “next” in order to finish the installation.

USB printer setup

If you wish to use a printer via the docking station, do not forget to change the printer port. You can do this by selecting the "Virtual printer port for USB" when installing the printer. If a printer has already been installed and you wish to connect it to the docking station, do not forget to change the port. You can do this by right-clicking in the Printers and faxes menu and selecting "server properties", which you can see in the window below.



Right-click and go to "server properties".



In the window that appears next, click on the second tab. You will see the following screen.

Here, you change the printer port to "Virtual printer port for USB". The printer now has the correct port in order to print.

Warranty

Any products under the Sweex brand are warranted for a period of three years. The Sweex Digital photo cameras, however, are warranted for two years. We do not grant support or warranties for any software and/or (rechargeable) batteries included. Warranty claims are only settled via the dealer where the product concerned was purchased.

The rightful owner has and retains title to all brand names and related rights mentioned on this packaging/in this manual.